

NSYDLM84P

Modular chassis DLM type for SPACIAL WM enclosure, 84 modules, H600xW600mm.



Main

| | |
|------------------------------------|---|
| Range | Spacial |
| Accessory / separate part category | Mounting accessory |
| Device application | Multi-purpose Modular distribution application |
| Product or component type | Chassis |
| Device short name | DLM |
| Enclosure nominal dimensions | |
| Mounting location | Step slide Front of enclosure |
| Range compatibility | Spacial CRN Spacial S3D Spacial S3X |
| Device composition | 1 chassis structure 2 finish cover 1 neutral/earth strip 2 x 16 mm ² 5 x 6 mm ² 3 front panels with 35 mm DIN rail |
| Quantity per set | Set of 1 |

Complementary

| | |
|-------------------------------|--|
| Material | Steel |
| Colour | Front panel : grey RAL 7035 |
| Surface finish | Polyester powder |
| Fixing mode | By fixing element - on front and back with supports location |
| Adjustment | In height from 40 to 85 mm for DIN rail |
| Number of horizontal rows | 3 |
| Total number of 18 mm modules | 84 |
| Type of front plate | Plain and cut-out plates |
| Number of cut-out | 3 cut-outs |
| Height | 553 mm |
| Width | 555 mm |
| Depth | 101.5 mm |

Environment

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 0940 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.