

High power contactor, TeSys Giga, 3 pole (3NO), AC-3 <=440V 330A, standard version, 100...250V wide band AC/DC coil

LC1G330KUEN

EAN Code: 3606481921970

Main

Range	TeSys	
Range of product	TeSys Giga	
Product or component type	Contactor	
Device short name	LC1G	
Contactor application	Power switching Motor control	
Utilisation category	AC-1 AC-3 AC-3e AC-4 AC-5a AC-5b AC-6a AC-6b AC-8a AC-8b DC-1 DC-3 DC-5	
Poles description	3P	
[Ue] rated operational voltage	<= 1000 V AC 50/60 Hz <= 460 V DC	
[le] rated operational current	440 A (at <40 °C) at <= 1000 V AC-1 330 A (at <60 °C) at <= 440 V AC-3	
[Uc] control circuit voltage	100250 V AC 50/60 Hz 100250 V DC	
Control circuit voltage limits	Operational: 0.8 Uc Min1.1 Uc Max (at <60 °C) Drop-out: 0.1 Uc Max0.45 Uc Min (at <60 °C)	

Complementary

[Uimp] rated impulse withstand voltage	8 kV
overvoltage category	III
[Ith] conventional free air thermal current	440 A (at 40 °C)
Rated breaking capacity	2940 A at 440 V
[lcw] rated short-time withstand current	2.65 kA - 10 s 1.8 kA - 30 s 1.3 kA - 1 min 0.9 kA - 3 min 0.75 kA - 10 min
Associated fuse rating	400 A aM at <= 440 V for motor 250 A aM at <= 690 V for motor

500 A gG at <= 690 V

Average impedance	0.000144 Ohm	
[Ui] rated insulation voltage	1000 V	
Power dissipation per pole	30 W AC-1 - Ith 440 A 16 W AC-3 - Ith 330 A	
Compatibility code	LC1G	
Pole contact composition	3 NO	
Auxiliary contact composition	1 NO + 1 NC	
Motor power kW	90 kW at 230 V AC 50/60 Hz (AC-3e) 160 kW at 400 V AC 50/60 Hz (AC-3e) 160 kW at 415 V AC 50/60 Hz (AC-3e) 185 kW at 440 V AC 50/60 Hz (AC-3e) 200 kW at 500 V AC 50/60 Hz (AC-3e) 220 kW at 690 V AC 50/60 Hz (AC-3e) 185 kW at 1000 V AC 50/60 Hz (AC-3e) 185 kW at 1000 V AC 50/60 Hz (AC-3e) 90 kW at 230 V AC 50/60 Hz (AC-3) 160 kW at 415 V AC 50/60 Hz (AC-3) 160 kW at 415 V AC 50/60 Hz (AC-3) 200 kW at 440 V AC 50/60 Hz (AC-3) 200 kW at 500 V AC 50/60 Hz (AC-3) 200 kW at 500 V AC 50/60 Hz (AC-3) 90 kW at 230 V AC 50/60 Hz (AC-3) 185 kW at 1000 V AC 50/60 Hz (AC-3) 160 kW at 440 V AC 50/60 Hz (AC-3) 185 kW at 1000 V AC 50/60 Hz (AC-3) 185 kW at 1000 V AC 50/60 Hz (AC-4) 160 kW at 440 V AC 50/60 Hz (AC-4) 185 kW at 440 V AC 50/60 Hz (AC-4) 200 kW at 500 V AC 50/60 Hz (AC-4) 220 kW at 690 V AC 50/60 Hz (AC-4)	
Motor power hp	100 hp at 200/208 V 60 Hz 125 hp at 230/240 V 60 Hz 250 hp at 460/480 V 60 Hz 300 hp at 575/600 V 60 Hz	
Irms rated making capacity	3830 A at 440 V	
Coil technology	Built-in bidirectional peak limiting	
Safety reliability level	B10d = 400000 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 3000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1	
Mechanical durability	8 Mcycles	
inrush power in VA (50/60 Hz, AC)	700 VA	
inrush power in W (DC)	645 W	
hold-in power consumption in VA (50/60 Hz, AC)	15.0 VA	
hold-in power consumption in W (DC)	9.1 W	
Operating time	4070 ms closing 1550 ms opening	
Maximum operating rate	600 cyc/h AC-3 600 cyc/h AC-3e 300 cyc/h AC-1 150 cyc/h AC-4	
Connections - terminals Connection pitch	Power circuit: bar 2 - busbar cross section: 32 x 10 mm Power circuit: lugs-ring terminals 1 185 mm² Power circuit: bolted connection Control circuit: push-in 1 0.22.5 mm² - cable stiffness: solid stranded without cable end Control circuit: push-in 1 0.252.5 mm² - cable stiffness: flexible with cable end Control circuit: push-in 2 0.51.0 mm² with cable end Control circuit: push-in 0.752.5 mm² - cable stiffness: solid stranded without cable end Control circuit: push-in 0.752.5 mm² - cable stiffness: flexible with cable end	
Connection pitch	45 mm	

Plate
EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1 IEC 60335-1:Clause 30.2 IEC 60335-2-40:Annex JJ UL 60335-1 UL 60335-2-40:Annex JJ
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
35 N.m
225 mm
140 mm
226 mm
7.5 kg

Environment

IP degree of protection	IP2X front face with shrouds conforming to IEC 60529 IP2X front face with shrouds conforming to VDE 0106	
Ambient air temperature for operation	-2560 °C	
Ambient air temperature for storage	-6080 °C	
Mechanical robustness	Vibrations 5300 Hz 2 gn contactor open Vibrations 5300 Hz 4 gn contactor closed Shocks 10 gn 11 ms contactor open Shocks 15 gn 11 ms contactor closed	
Colour	Dark grey	
Protective treatment	TH	
Permissible ambient air temperature around the device	-4070 °C at Uc	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	31.000 cm
Package 1 Width	22.500 cm
Package 1 Length	31.000 cm
Package 1 Weight	7.473 kg
Unit Type of Package 2	S06
Number of Units in Package 2	4
Package 2 Height	105.000 cm
Package 2 Width	60.000 cm
Package 2 Length	80.000 cm
Package 2 Weight	40.500 kg

Logistical informations

Country of origin

CN

Contractual warranty

Warranty

18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

∇ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	1442
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
SCIP Number	6fbdad13-bb7c-47d4-a6d6-d82dd6f54349
REACh Regulation	REACh Declaration
China RoHS Regulation	China RoHS declaration
PVC free	Yes

Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Halogen content performance	Halogen free plastic parts product
Take-back	No

Product datasheet

LC1G330KUEN

Installation

Installation Videos

TeSys Giga - How to install the auxiliary contact block

TeSys Giga - How to install and remove remote wear diagnosis module

TeSys Giga - How to install mechanical interlock kit

TeSys Giga - How to install cable memory kit

TeSys Giga - How to directly mount LR9G overload relay

TeSys Giga - How to replace control module

TeSys Giga - How to replace switching modules

TeSys Giga - How to assemble reverser solution

TeSys Giga - How to assemble change-over solution