Specifications

Eaton 136506

Eaton Moeller® series ZEB Overload relay, Direct mounting, Earth-fault protection: none, Ir= 20 - 100 A, 1 N/O, 1 N/C ZEB150-100

General specificatio	ns
PRODUCT NAME	Eaton Moeller® series ZEB Electronic overload relay
CATALOG NUMBER	136506
MODEL CODE	ZEB150-100
EAN	4015081332861
PRODUCT LENGTH/DEPTH	140.5 mm
PRODUCT HEIGHT	120 mm
PRODUCT WIDTH	56 mm
PRODUCT WEIGHT	0.74 kg
CERTIFICATIONS	UL File No.: E1230 CSA IEC/EN 60947 UL CSA Class No.: 3211-03 VDE 0660 UL Category Control No.: NKCR CSA-C22.2 No. 14 UL 508 CSA File No.: 2290956 IEC/EN 60947-4-1 CE
CATALOG NOTES	Rated operational current: Switch-on and switch-off conditions based on DC- 13, time constant as specified.



Features & Functions	S
EARTH FAULT PROTECTION	None
FEATURES	Phase-failure sensitivity (according to IEC/EN 60947, VDE 0660 Part 102)
FUNCTIONS	Filament bulb (24 V)

General	
CLASS	Adjustable
DEGREE OF PROTECTION	IP20
MOUNTING METHOD	Direct attachment Direct mounting
OVERLOAD RELEASE CURRENT SETTING - MIN	20 A
OVERLOAD RELEASE CURRENT SETTING - MAX	100 A
OVERVOLTAGE CATEGORY	III
POLLUTION DEGREE	3
PRODUCT CATEGORY	Electronic overload relays ZEB
PROTECTION	Finger and back-of-hand proof, Protection against direct contact when actuated from front (EN 50274)
RATED IMPULSE WITHSTAND VOLTAGE (UIMP)	6000 V (auxiliary circuits) 6000 V AC
SHOCK RESISTANCE	Mechanical, According to IEC/EN 60068-2-27 15 g, Mechanical, According to IEC/EN 60068-2-27, Shock duration 10 ms
SUITABLE FOR	Branch circuits, (UL/CSA)
VOLTAGE TYPE	Self powered
	·

Climatic environmental conditions	
AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
AMBIENT OPERATING TEMPERATURE - MAX	65 °C
AMBIENT OPERATING TEMPERATURE (ENCLOSED) - MAX	45 °C
CLIMATIC PROOFING	Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30

Terminal capacities	
TERMINAL CAPACITY (FLEXIBLE WITH FERRULE)	2 x (0.75 - 2.5) mm², Control circuit cables
TERMINAL CAPACITY (SOLID)	1 x (16 - 50) mm², Main cables 2 x (0.75 - 4) mm², Control circuit cables
TERMINAL CAPACITY (SOLID/STRANDED AWG)	1 x (6 - 1), Main cables 2 x (18 - 12), Control circuit cables
STRIPPING LENGTH (MAIN CABLE)	14 mm
STRIPPING LENGTH (CONTROL CIRCUIT CABLE)	8 mm

SCREW SIZE	M3.5, Terminal screw, Control circuit cables
SCREWDRIVER SIZE	1 x 6 mm, Terminal screw, Control circuit cables, Standard screwdriver 2, Terminal screw, Control circuit cables, Pozidriv screwdriver
TIGHTENING TORQUE	0.8 - 1.2 Nm, Screw terminals, Control circuit cables 7 lb-in, Screw terminals

Electrical rating	
CONVENTIONAL THERMAL CURRENT ITH OF AUXILIARY CONTACTS (1-POLE, OPEN)	5 A
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	0 V
RATED FREQUENCY - MIN	50 Hz
RATED FREQUENCY - MAX	60 Hz
RATED OPERATIONAL CURRENT (IE) AT AC-15, 120 V	1.5 A
RATED OPERATIONAL CURRENT (IE) AT AC-15, 220 V, 230 V, 240 V	1.5 A
RATED OPERATIONAL CURRENT (IE) AT AC-15, 380 V, 400 V, 415 V	0.9 A
RATED OPERATIONAL CURRENT (IE) AT DC-13, 110 V	0.4 A
RATED OPERATIONAL CURRENT (IE) AT DC-13, 220 V, 230 V	0.2 A
RATED OPERATIONAL CURRENT (IE) AT DC-13, 24 V	0.9 A
RATED OPERATIONAL CURRENT (IE) AT DC-13, 60 V	0.75 A
RATED OPERATIONAL VOLTAGE (UE) AT AC -	690 V

Contacts	
NUMBER OF AUXILIARY CONTACTS (CHANGE- OVER CONTACTS)	0
NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	1
NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	1
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	1
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	1

MAX	
SHORT-CIRCUIT PROTECTION RATING	Max. 6 A gG/gL, fuse, Without welding, Auxiliary and control circuits
SHORT-CIRCUIT CURRENT RATING (HIGH FAULT AT 600 V)	100 kA, Fuse, SCCR (UL/CSA) 200 A, Class J, max. Fuse, SCCR (UL/CSA)
SWITCHING CAPACITY (AUXILIARY CONTACTS, PILOT DUTY)	B600, AC operated (UL/CSA) R300, DC operated (UL/CSA)
VOLTAGE RATING - MAX	600 V

Design verification	
EQUIPMENT HEAT DISSIPATION, CURRENT- DEPENDENT PVID	25.4 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT- DEPENDENT PVID	8.47 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	100 A
STATIC HEAT DISSIPATION, NON- CURRENT-DEPENDENT PVS	0 W
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.

ETIM only	
ELECTRICAL CONNECTION TYPE OF MAIN CIRCUIT	Screw connection
ADJUSTABLE CURRENT RANGE - MIN	20 A
ADJUSTABLE CURRENT RANGE - MAX	100 A
RESET FUNCTION	Automatic Push-button

Does not apply, since the entire switchgear needs to be evaluated.
ls the panel builder's responsibility.
Is the panel builder's responsibility.
Is the panel builder's responsibility.
ls the panel builder's responsibility.
Is the panel builder's responsibility.
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
Is the panel builder's responsibility. The specifications for the switchgear must be observed.
Is the panel builder's responsibility. The specifications for the switchgear must be observed.
The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Resources	
BROCHURES	eaton-motor-starters- system-xstart-brochure- br03407001en-en-us.pdf
	Electronic overload relay ZEB
	eaton-tripping-devices- zeb-overload-relay- characteristic-curve.eps
DRAWINGS	eaton-tripping-devices- zeb-overload-relay- dimensions-006.eps
	eaton-tripping-devices- zeb-overload-relay-3d- drawing.eps
ECAD MODEL	ETN.136506.edz
INSTALLATION INSTRUCTIONS	IL04210002E
	zeb150 10 9468.stp
MCAD MODEL	zeb150_100_kk.dwg
	<u>zeb150_100.stp</u>
WIRING DIAGRAMS	eaton-tripping-devices- overload-relay-zb- overload-relay-wiring- diagram.eps
	eaton-general-release-zeb- overload-relay-wiring- diagram.eps

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc

Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

 $\hbox{@ 2025 Eaton.}$ All Rights Reserved.

Follow us on social media to get the latest product and support information.









